

# MB4052

## 4-CHANNEL 8-BIT A/D CONVERTER

### 4-CHANNEL 8-BIT A/D CONVERTER SUBSYSTEM

The Fujitsu MB 4052 is an analog-to-digital general purpose converter (ADC) that features four channels of analog inputs and an 8-bit data length of digital output. The analog input signal is converted to serial 8-bit digital data by the successive approximation technique which provides high-speed conversion; i.e., a large amount of analog data can be converted within a short time.


All digital I/O signals, including control inputs, are TTL-level compatible to provide wide applications such as in microprocessor-controlled systems, etc.

- Single power supply
  - DIP: +3.5V to +6.0V or +8.0V to +1 8V (with internal regulator)
  - FPT: +3.5V to +6.0V or +8.0V to +13.2V (with internal regulator)
- Multiplex 4-channel analog inputs
- Changeable analog input voltage ranges:
  - 0 to 2.5V (standard mode: RS = 1)
  - 0 to 0.625V (contracted mode: RS = 0)
  - 0 to 10V (expanded mode: through built-in divider)
- Analog input bias current: 250 nA maximum
- Resolution: 8 bits
- Linearity: 0.19% maximum
- Successive approximation conversion: 100 s/ch maximum at  $f_{CLK} = 100$  kHz
- Ratio-metric conversion by reference voltage  $V_{CC1}$
- Serial data output (open-collector)
- TTL/CMOS compatible digital I/O
- Package: DIP-16C-C02  
DIP-16P-M04  
FPT-16P-M03


### ABSOLUTE MAXIMUM RATINGS (All Voltages referenced to A.G/D.G)

Rating	Symbol	Value	Unit
Power supply voltage	$V_{CC1}$	+7.0	V
	$V_{CC2}$	+20	
Digital input voltage	$V_{ID}$	-0.5 to +20	V
Digital output voltage (off-state)	$V_{OH}$	+20	V
Analog input voltage	$V_{IA}$	$V_{CC1} + 0.5$	V
Storage temperature — ceramic	$T_{STG}$	-55 to +150	°C
Storage temperature — plastic	$T_{STG}$	-40 to +125	°C


Note: Permanent device damage may occur if the above Absolute Maximum Ratings are exceeded. Functional operation should be restricted to the conditions as detailed in the operational sections of this data sheet. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.



CERAMIC PACKAGE  
DIP-16C-C02




PLASTIC PACKAGE  
DIP-16P-M04



PLASTIC PACKAGE  
FPT-16P-M03

### PIN ASSIGNMENT



This device contains circuitry to protect the inputs against damage due to high static voltages or electric fields. However, it is advised that normal precautions be taken to avoid application of any voltage higher than maximum rated voltages to this high impedance circuit.




Figure 1. MB4052 Block Diagram

RECOMMENDED OPERATING CONDITIONS

(T <sub>A</sub> =305°C to +85°C )						
Parameter	Symbol		Value			Unit
			Min	Typ	Max	
Power supply voltage	V <sub>CC1</sub>		3.5	5.0	6.0	V
	V <sub>CC2</sub>	DIP	8.0	12.0	18.0	V
		FPT	8.0	12.0	13,2	V
Digital output low current	I <sub>OL</sub>		—	—	8	mA
Operating temperature	T <sub>A</sub>		−30	—	+85	°C

## PIN DESCRIPTIONS

### Input for Voltage Range Expansion (Ex 2), Pin 2

This input pin is provided to expand the voltage range of analog input signal. This input pin is connected to the internal one-to-four voltage divider which reduces an analog signal level to one fourth of input level.

### Output for Voltage Range Expansion (Ex 1), Pin 3

This output pin is provided to expand the allowable analog input level in cooperation with the above EX 2 pin. A reduced signal which is divided in the internal divider is output on this pin.

This output pin can be connected to any of standard analog inputs  $A_0$ ,  $A_1$ ,  $A_2$  or  $A_3$  so that the EX 2 pin can function as one of four channel inputs.

### Analog Inputs ( $A_0$ to $A_3$ ), Pins 4, 5, 6, and 7

These input pins are provided to receive four channels of analog inputs. One of these four channels is selected by a combination of  $C_0$  and  $C_1$  inputs.

### Channel Select ( $C_1$ and $C_0$ ), Pins 9 and 10

These control inputs are used to designate one of four analog inputs as shown in the following channel selection table

$C_1$	$C_2$	Channel
0	0	$A_0$
0	1	$A_1$
1	0	$A_2$
1	1	$A_3$

### Chip Select ( $\overline{CS}$ ), Pin 11

This control input pin is used to start analog-to-digital conversion. When  $\overline{CS}$  goes low, the A/D conversion starts and the DATA OUT output is enabled. When an A/D conversion is completed or termination of conversion is required,  $\overline{CS}$  is made high.

### A/D Conversion Clock (ADC CLK), Pin 12

This clock signal is input to the internal successive approximation register and used as timing signal for A/D conversion. The conversion speed of this device is determined by the clock rate. Ten clock cycles are required for a complete 8-bit conversion. A precise cycle time is not always required for this clock signal.

### Data Output (DATA OUT), Pin 13

This output pin is provided to output A/D conversion results as digital signals. The converted digital data is serially output in the order of start bit MSB (most significant bit), 2SB (second significant bit), ..., 7SB, LSB (least significant bit) and stop-bit in synchronization with the ADC CLK clock signal.

### Range Select (RS), Pin 14

This control input is provided to select an analog input voltage range as shown in the following range selection table. This input must not be changed during an A/D conversion.

RS	Voltage Range
0	0 to $1/8 V_{CC1}$
1	0 to $1/2 V_{CC1}$

### Analog Ground (AG) and Digital Ground (DG), Pins 1 and 8

These are terminals for ground. The analog circuitry and digital circuitry have separate ground terminals, respectively.

### Power Supplies ( $V_{CC2}$ and $V_{CC1}$ ), Pins 15 and 16

When the device operates within a voltage range of 3.5V to 6.0V, the power source is connected to  $V_{CC1}$ , which is shorted to  $V_{CC2}$ . When the device operates within a voltage range of 8V to 18V for DIP packages and 8V to 13.2V for Flat packages, the power source is connected to  $V_{CC2}$ .

In this high voltage operation mode, the  $V_{CC1}$  pin is used as an output pin which supplies +5V stabilized voltage and 10-mA load current and the supplied voltage is regulated in the internal voltage regulator.  $V_{CC1}$  is used as the reference voltage of A/D conversion, regardless of the type of voltage.

**ANALOG CIRCUIT CHARACTERISTICS FOR DIP PACKAGE**
 $(V_{CC1} = V_{CC2} = 3.5V \text{ to } 6.0V, T_A = 30^\circ C \text{ to } +85^\circ C)$ 

Parameter		Symbol	Condition	Value			Unit
				Min	Typ	Max	
Resolution			—	—	—	8	Bit
Linearity Error			$V_{CC1} = 5V$	—	—	$\pm 0.5$	LSB
Differential Linearity Error				—	—	$\pm 0.9$	LSB
Zero Transition Voltage	Contracted Range	$V_{ZC}$	$V_{CC1} = 5V, T_A = 25^\circ C$	0	6	16	mV
	Standard Range	$V_{ZS}$		7	17	27	mV
	Expanded Range	$V_{ZE}$		22	62	102	mV
Full Scale Transition Voltage	Contracted Range	$V_{FC}$		600	625	650	mV
	Standard Range	$V_{FS}$		2.475	2.500	2.525	V
	Expanded Range	$V_{FE}$		9.600	10.000	10.400	V
Comparator Input Current		$I_{IC}$	$V_{CC1} = 5V$	-250	-100	—	nA
Divider Input Resistance for Expanded Range		$R_{INE}$	—	5	10	15	k $\Omega$
Regulator	Output Voltage	$V_{OR}$	$8V \leq V_{CC2} \leq 18V$	4.5	5.0	5.5	V
	Line Regulation			—	4.0	—	mV/V
	Load Regulation		$V_{CC2} = 12V,$ $0 \text{ mA} \geq I_{OUT} \geq -10 \text{ mA}$	—	0.5	—	mV/mA
	Output Voltage Temperature		$V_{CC2} = 12V$	—	50	—	ppm/ $^\circ C$
Conversion Cycle Time		$t_{CYC}$	$f_{CLK} = 100 \text{ kHz}$	—	—	100	$\mu s/ch$

A minus sign (–) prefixed to a current value indicates that the current flows from the IC to the external circuit.

## ANALOG CIRCUIT CHARACTERISTICS FOR CERAMIC DIP PACKAGE

(V<sub>CC1</sub> = V<sub>CC2</sub> = 3.5V to 6.0V, T<sub>A</sub> = 30°C to +85°C)

Parameter		Symbol	Condition	Value			Unit
				Min	Typ	Max	
Resolution			—	—	—	8	Bit
Linearity Error			V <sub>CC1</sub> = 5V	—	—	±0.4	LSB
Differential Linearity Error				—	—	±0.8	LSB
Zero Transition Voltage	Contracted Range	V <sub>ZC</sub>	V <sub>CC1</sub> = 5V, T <sub>A</sub> = 25°C	0	6	16	mV
	Standard Range	V <sub>ZS</sub>		7	17	27	mV
	Expanded Range	V <sub>ZE</sub>		22	62	102	mV
Full Scale Transition Voltage	Contracted Range	V <sub>FC</sub>		610	625	640	mV
	Standard Range	V <sub>FS</sub>		2.480	2.500	2.520	V
	Expanded Range	V <sub>FE</sub>		9.760	10.000	10.240	V
Comparator Input Current		I <sub>IC</sub>	V <sub>CC1</sub> = 5V	−250	−100	—	nA
Divider Input Resistance for Expanded Range		R <sub>INE</sub>	—	5	10	15	kΩ
Regulator	Output Voltage	V <sub>OR</sub>	8V ≤ V <sub>CC2</sub> ≤ 18V	4.5	5.0	5.5	V
	Line Regulation			—	4.0	—	mV/V
	Load Regulation		V <sub>CC2</sub> = 12V, 0 mA ≥ I <sub>OUT</sub> ≥ −10 mA	—	0.5	—	mV/mA
	Output Voltage Temperature		V <sub>CC2</sub> = 12V	—	50	—	ppm/°C
Conversion Cycle Time		t <sub>CYC</sub>	f <sub>CLK</sub> = 100 kHz	—	—	100	μs/ch

A minus sign (−) prefixed to a current value indicates that the current flows from the IC to the external circuit.

## ANALOG CIRCUIT CHARACTERISTICS FOR PLASTIC FLAT PACKAGE

(V<sub>CC1</sub> = V<sub>CC2</sub> = 3.5V to 6.0V, T<sub>A</sub> = 30°C to +85°C)

Parameter		Symbol	Condition	Value			Unit
				Min	Typ	Max	
Resolution			—	—	—	8	Bit
Linearity Error			V <sub>CC1</sub> = 5V	—	—	±0.4	LSB
Differential Linearity Error				—	—	±0.8	LSB
Zero Transition Voltage	Contracted Range	V <sub>ZC</sub>	V <sub>CC1</sub> = 5V, T <sub>A</sub> = 25°C	0	6	16	mV
	Standard Range	V <sub>ZS</sub>		7	17	27	mV
	Expanded Range	V <sub>ZE</sub>		22	62	102	mV
Full Scale Transition Voltage	Contracted Range	V <sub>FC</sub>		600	625	650	mV
	Standard Range	V <sub>FS</sub>		2.475	2.500	2.525	V
	Expanded Range	V <sub>FE</sub>		9.600	10.000	10.400	V
Comparator Input Current		I <sub>IC</sub>	V <sub>CC1</sub> = 5V	−250	−100	—	nA
Divider Input Resistance for Expanded Range		R <sub>INE</sub>	—	4.5	5.0	15	kΩ
Regulator	Output Voltage	V <sub>OR</sub>	8V ≤ V <sub>CC2</sub> ≤ 13.2V	4.5	5.0	5.5	V
	Line Regulation			—	4.0	—	mV/V
	Load Regulation		V <sub>CC2</sub> = 12V, 0 mA ≥ I <sub>OUT</sub> ≥ −2 mA	—	0.5	—	mV/mA
	Output Voltage Temperature		V <sub>CC2</sub> = 12V	—	50	—	ppm/°C
Conversion Cycle Time		t <sub>CYC</sub>	f <sub>CLK</sub> = 100 kHz	—	—	100	μs/ch

A minus sign (−) prefixed to a current value indicates that the current flows from the IC to the external circuit.

## DIGITAL CIRCUIT DC CHARACTERISTICS

(V<sub>CC1</sub> = V<sub>CC2</sub> = 3.5V to 6.0V, T<sub>A</sub> = 30°C to +85°C)

Parameter	Symbol	Condition	Value			Unit
			Min	Typ	Max	
Input Clamp Voltage	V <sub>IC</sub>	V <sub>CC1</sub> = 3.5, I <sub>IL</sub> = 18 mA	—	—	−1.5	V
High Level Input Current	I <sub>OH</sub>	V <sub>CC1</sub> = 3.5V, V <sub>IH</sub> = 2.0V, V <sub>IL</sub> = 0.8V, I <sub>OH</sub> = 20V	—	—	100	μA
Low Level Output Voltage	V <sub>OL1</sub>	V <sub>CC1</sub> = 3.5V, V <sub>IH</sub> = 2.0V, V <sub>IL</sub> = 0.8V, I <sub>OL</sub> = 4 mA	—	—	0.4	V
	V <sub>OL2</sub>	V <sub>CC1</sub> = 3.5V, V <sub>IH</sub> = 2.0V, V <sub>IL</sub> = 0.8V, I <sub>OL</sub> = 8 mA	—	—	0.5	V
High Level Input Current	I <sub>IH1</sub>	V <sub>CC1</sub> = 6.0V, V <sub>IH</sub> = 2.7V	—	—	20	μA
Low Level Input Current	I <sub>IL</sub>	V <sub>CC1</sub> = 6.0V, V <sub>IH</sub> = 20V	—	—	100	μA
Power Supply Current for V <sub>CC1</sub>	I <sub>CC1</sub>	V <sub>CC1</sub> = 6.0V	—	15*		μA
Power Supply Current for V <sub>CC2</sub>	I <sub>CC2</sub>	V <sub>CC1</sub> = Open, V <sub>CC2</sub> = 20V for DIP Package V <sub>CC2</sub> = 13.2V for Flat Package	—	15	25	mA

\*This typical value is measured at V<sub>CC1</sub> = 5.0V and T<sub>A</sub> = 25°C.

A minus sign (−) prefixed to a current value indicates that the current flows from the IC to the external circuit.

The values are measured at V<sub>CC1</sub> = V<sub>CC2</sub> except the I<sub>CC2</sub> parameter.

## DIGITAL CIRCUIT AC CHARACTERISTICS

(V<sub>CC1</sub> = V<sub>CC2</sub> = 3.5V to 6.0V, T<sub>A</sub> = 30°C to +85°C)

Parameter	Symbol	Value			Unit
		Min	Typ	Max	
ADC CLK Cycle Time	t <sub>CY</sub>	10	—	—	μs
ADC CLK H Level Pulse Width	t <sub>WAC+</sub>	2.5	—	—	μs
ADC CLK L Level Pulse Width	t <sub>WAC−</sub>	2.5	—	—	μs
CS H level Pulse Width	t <sub>WCS+</sub>	1.5	—	—	μs
CS Setup Time	t <sub>SCS</sub>	1	—	—	μs
CS Hold Time	t <sub>HCS</sub>	1	—	—	μs
Channel Setup Time	t <sub>SCH</sub>	0	—	—	μs
Channel Hold Time	t <sub>HCH</sub>	1	—	—	μs
Propagation Delay Time	t <sub>PLH</sub> t <sub>PHL</sub>	—	800	2,000	ns




Figure 2. AC Characteristics Waveform




Figure 3. Timing Diagram








Figure 4. Load Conditions

## TYPICAL WAVEFORMS OF PROPAGATION DELAY


$t_{PLH}$  (Data Out Transition from low-level to high-level)




$t_{PHL}$  (Data Out Transition from high-level to low-level)



## TYPICAL CONVERSION WAVEFORM





Condition  
 $f_{CLK} = 100kHz$   
 $V_{CC1} = 5V$   
 Standard Range  
 $V_{IA} \doteq 1663 mV$




**Figure 5. Example of Expand Range Mode Connection**

## PACKAGE DIMENSIONS



# PACKAGE DIMENSIONS (Continued)



All Rights Reserved. Circuit diagrams utilizing Fujitsu products are included as a means of illustrating typical semiconductor applications. Complete information sufficient for construction purposes is not necessarily given. The information contained in this document has been carefully checked and is believed to be reliable. However, Fujitsu assumes no responsibility for inaccuracies.

The information contained in this document does not convey any license under the copyrights, patent rights or trademarks claimed and owned by Fujitsu. Fujitsu reserves the right to change products or specifications without notice. No part of this publication may be copied or reproduced in any form or by any means, or transferred to any third party without prior written consent of Fujitsu.

## FUJITSU LIMITED

For further information please contact:

### Japan

FUJITSU LIMITED  
Integrated Circuits and Semiconductor Marketing  
Furukawa Sogo Bldg., 6-1, Marunouchi 2-chome  
Chiyoda-ku, Tokyo 100, Japan  
Tel: (03) 3216-3211  
Telex: 781-2224361  
FAX: (03) 3216-9771

### North and South America

FUJITSU MICROELECTRONICS, INC.  
Semiconductor Division  
3545 North First Street  
San Jose, CA 95134-1804 USA  
Tel: 408-922-9000  
Telex: 910-671-4915  
FAX: 408-432-9044

### Europe

FUJITSU MIKROELEKTRONIK GmbH  
Arabella Centre 9.0G  
Lyoner Strasse 44-48  
D-6000 Frankfurt 71  
F.R. Germany  
Tel: (069) 66320  
Telex: 411963 FAX: (069) 6632122

### Asia

FUJITSU MICROELECTRONICS ASIA PTE LIMITED  
51 Bras Basah Road,  
Plaza By The Park,  
#06-04/07,  
Singapore 0718  
Tel: 336-1600  
Telex: 55573 FAX: 336-1609